

DMC 1000 WORKSHEETS

Default settings and worksheets

Table A1 – Media Library Setup Menu

| Setting | Default | Your Settings |
|------------------------------|----------------------|---------------|
| Auto Disc Insert Preferences | Play & Record | |
| Audio Encoding Quality | MP3 192kbps (Medium) | |

Table A2 – DVD Player Setup Menu

| Setting | Default | Your Settings |
|-----------------------------|----------|---------------|
| Preferred Subtitle Language | Off | |
| Preferred Audio Language | English | |
| Parental Control Level | Off | |
| Video Presentation Mode | Original | |
| Dynamic Range Compression | Off | |
| DVD Bass Management | Off | |

Table A3 – Audio Setup Menu

| Setting | Default | Your Settings |
|--------------------------|--|--|
| Speaker Setup | Front L & R: Large Surround L & R: Large Center: Large Subwoofer: Yes | Front L & R: Surround L & R: Center: Subwoofer: |
| Digital Audio Out Format | Compressed | |
| HDMI Audio Out | Auto | |

Table A4 – Video Setup Menu

| Setting | Default | Your Settings |
|-------------------|---|---------------|
| Video Output | Depends on physical connections | |
| Output Resolution | Depends on physical connections: Analog (composite or S-video): 480i Analog (component): 480p HDMI: Auto | |

Table A5 – General Setup Menu

NOTE: These settings are not adjusted in normal use.

| Setting | Purpose | Your Settings |
|--------------------|--|-----------------------------|
| Software Update | If a system software upgrade becomes available in the future, download it to a CD and follow the instructions here | Not used |
| Date & Time | Set system date and time after a reset | Adjusted only after a reset |
| System Information | Displays software version and hard-disc drive usage | Not used |

DMC 1000 WORKSHEETS

Table A6 – Advanced Setup Menu

| Setting | Purpose | Your Settings |
|------------------------|--|---|
| Backup | Backs up hard-disc drive as a precaution | After your custom installer transfers your music collection to the Media Library, he or she should back it up as a precaution |
| Restore | In case the hard-disc drive is replaced, restores the Media Library from the last version that was backed up | Keep your backup of the Media Library updated |
| Reset Factory Defaults | System reset | Use only as a last resort; requires reconfiguring all system settings (the Media Library's contents are not affected) |
| Network | Displays network identification parameters | Ethernet: IP Address: Subnet Mask: Gateway Address: DNS 1: DNS 2: Proxy Address: Proxy Port Number: |
| Language Selected | Sets system display language; default is English | |
| Format USB | Reformats a USB device, erasing all content | Exercise extreme caution before using this command |

Table A7 – Power Modes

| Power Mode | Indicator | Functionality | Front-Panel Power Control | Remote Control Power On | Remote Control Power Off |
|---------------|-------------|--|--|--|--|
| Full-Off Mode | Dim blue | System powered down | System boots and goes to Full-Power Mode | System boots and goes to Full-Power Mode | No action |
| Sleep Mode | Amber | Standby; unit is ready for quick turn-on | Full-Power Mode | Full-Power Mode | No action |
| Server Mode | Amber | Remote-zone and network control available; on-screen menus off | Full-Power Mode | Full-Power Mode | Sleep Mode |
| Full-Power | Bright blue | Operates normally | Single press → Server Mode Press and hold → Full-Off Mode | No action | Single press → Server Mode Press and hold → Full-Off Mode |