



HK 3470

STEREO RECEIVER

High fidelity is both an ideal and a philosophy. Harman Kardon pioneered the high-fidelity stereo receiver more than forty-five years ago, and our commitment to sonic purity has never wavered. The HK 3470, our top-of-the-line stereo receiver, combines a 2 x 100-watt, high-current, ultrawide-bandwidth amplifier design with our proprietary VMAx® processor to generate dramatic 3-D sound fields from two-channel sources with only two speakers. And with remote A/B speaker selection, a programmable universal remote, as well as infrared extension jacks, it's among the easiest to use receivers we've ever built. The HK 3470 is the ultimate realization of high fidelity.

harman/kardon®
Power for the Digital Revolution.™

phono input
ultrawide bandwidth

A/B speaker selection

VMAx

high-current capability

subwoofer output

programmable remote

tape monitor loop





HK 3470

STEREO RECEIVER

Specifications

- Continuous Average Power (FTC): 100 watts x 2 @ 8 ohms (20Hz – 20kHz, <0.07% THD, both channels driven); High-Current Capability: ± 45 amps
- Tuner – Usable Sensitivity: IHF 1.12 μ V/13.5dBf; THD at 1kHz with 100% Modulation: (Mono) 0.3%, (Stereo) 0.4%; FM Adjacent Channel Selectivity: ± 400 kHz, 65dB; Ultimate (Maximum) S/N Ratio (measured at 1mV RF Input Level): (Mono) 73dB, (Stereo) 72dB
- General – Dimensions (H x W x D): 6-1/8" x 17-3/8" x 16-5/16" (156mm x 442mm x 415mm); Weight: 26.8 lb (12.1kg)

[NOTE: Depth measurement includes knobs, buttons and terminal connections; height measurement includes feet and chassis.] All features and specifications are subject to change without notice.

Features

100W x 2 Into 8 Ohms,
20Hz – 20kHz at <0.07%
THD, Both Channels Driven
Simultaneously • High-Current
(± 45 Amps) Capability
Amplifier • Ultrawide-Bandwidth
Amplifier Design • VMAx
Virtual Surround Sound Delivers
an Enveloping Sound Field
With Only Two Speakers • Five
Audio Inputs • High-Quality
Phono Input • Tape Monitor
Loop • Preamp Out/Main
Amp Input Jacks for Use With
Outboard Equalizers • Subwoofer
Output • Remote A/B Speaker
Switching • FM Stereo/FM/AM
Tuner With 30 Station Presets and
Direct-Access Tuning • IR Remote
Extension Jacks • Programmable
Learning Remote

harman/kardon®
Power for the Digital Revolution.™

250 Crossways Park Drive
Woodbury, NY 11797
800-422-8027 FAX 516-682-3523
www.harmankardon.com

H A Harman International Company